BExH120 'Hootronic' Explosion Proof Alarm Horn

The flameproof BExH120 Hootronic Siren is suitable for Zone 1, 2, 21 & 22 applications. Approved to IECEx, ATEX, Ex EAC and INMETRO standards. The BExH120 authentically reproduces the traditional sounds of electro-mechanical devices whilst providing a significantly higher level of performance and reliability.

The E2S Hootronic series of products faithfully reproduce the sounds made by legacy electromechanical signalling devices but in a modern, reliable and cost effective way. With output levels of up to 117.5dB(A) at 1 metre the BExH120 surpasses legacy electro-mechanical devices in performance and effectiveness, it is also continuously rated, requires zero maintenance and the signal quality will not degrade with age.

Features

- Marine grade, corrosion proof, LM6 aluminium enclosure.
- Ingress protection IP66/67
- Stainless steel fixings
- Dual M20 cable entries adaptors available.
- Stopping plug included.
- Reverse polarity diode fitted.
- Very large termination area.
- Ratchet adjustable stainless steel 'U' bracket.
- Sound level ouputs up to 117.5dB(A) at 1 metre with

a choice of 5 alarm sounds combining the signalling power of mutliple electro-mechanical products in one unit:

1.Industrial Hooter

2. High Frequency Mechanical Siren

3. Medium Frequency Mechanical Siren

4. Electro Mechanical Buzzer

5.Mechanical Bell

Approvals

- IECEX KEM 10.0003X
- ATEX KEMA 99ATEX6312X
- TR-CU Ex EAC certificate: RU C-GB.AA71.B.00109
- INMETRO certificate: 10-IEx-0009

Coding

- II 2G Ex db IIB T4 Ta -50° to +70°C
- II 2G Ex db IIC T4 Ta -50° to +55°C
- II 2D Ex tb IIIC T100°C Db Ta -50°C to +55°C
- II 2D Ex tb IIIC T115°C Db Ta -50°C to +70°C


















Specification

Nominal output:	117.5dB(A) @ 1m +/- 3dB - Tone 4 [108.5dB(A) @ 10ft/3m]
No. of tones:	5
No. of stages:	3
Volume control:	Yes
Effective range:	200m/656ft @ 1KHz
Voltages DC:	24vdc
Voltages AC:	115vac; 230vac
Stage switching:	Negative
Ingress protection:	IP66/67
Enclosure matl:	Marine grade copper free LM6 Aluminium
Enclosure finish:	Chromate & powder coated finish - anti-corrosion.
Colour:	RAL3000 Red Grey RAL7038 Special – available on request
BExH120 horn:	High impact UL94 VO & 5VA FR ABS
Cable entries:	Dual M20 ISO (one stopping plug inc)
Terminals:	0.5 - 2.5mm² (20-14 AWG)
Enclosure volume:	<2 litres
Line monitoring:	Blocking diode included EOL Min. 500 Ohm 2w, or 3k3 Ohm 0.5w resistor or diode (DC versions) can be fitted
Relative humidity:	95% – Additional tropicalisation is recommended for applications where both high relative humidity and high ambient temperatures exist
Weight:	DC: 3.20kg/7.04lbs AC: 3.40kg/7.48lbs
*SPL data +/-3dB(A	A). Measured at optimum voltage.

P	arl	С	o d	es
			U U	03

Version:	Part code:	
Product type:	BExH 120	Explosion proof Hootronic Alarm
Туре:	DF	Ex d, Flare re-entrant horn
Voltage:	DC024 AC115 AC230	24V dc 115V ac 240V ac
Cable Entry Type: [e]	A B C D E F G	$2 \times M20x1.5mm$ $2 \times 1/2'' NPT - adaptors$ $2 \times 3/4'' NPT - adaptors$ $2 \times M25x1.5mm - adaptors$ $1 \times 1/2'' NPT - adaptor$ $1 \times 3/4'' NPT - adaptor$ $1 \times M25x1.5mm - adaptor$
Adaptor/Stopping plug material: [m]		Brass Nickel Plated Stainless Steel
Bracket matl & tag: [s]	1 2 3 4	A2 304 Stainless Steel A4 316 Stainless Steel A2 304 St/St with Equip. Tag A4 316 St/St with Equip. Tag (304)
Product version: [v]A1	Default – IECEx, ATEX, Ex EAC & INMETRO
Enclosure colour: [X]	R G S	Red RAL3000 Grey RAL7038 Special – contact E2S
Accessories:	SP65-0001-A2 SP65-0001-A4 SP65-0003-A2 SP65-0003-A4	Pole Mount Bracket Kit 2'' St/St A2 (304) Pole Mount Bracket Kit 2'' St/St A4 (316) Sunshade – St/St A2 (304) Sunshade – St/St A4 (316)

Current Consumption

Voltage:		Max. I/P Volts:	Current:
24V dc		30V dc	400mA
115V ac	50/60Hz	126.5V ac	130mA
230V ac	50/60Hz	253V ac	65mA

Tone table				
S 1 T 1	Description Industrial Hooter	S 2 S 3 T 3 T 5		
Т2	High Frequency Mechanical Siren	Т1 Т5		
Т3	Medium Frequency Mechanical Siren	Т1 Т5		
T 4	Electro Mechanical Buzzer	T 2 T 5		
T 5	Mechanical Bell	Т1 Т2		